

094	PF	Peaking Frequency PF1-PF0 = 0 (2.7 Mhz) 1 (3.1 Mhz) 2 (3.5 Mhz) 3 (spare)	0-3	2
095	APSSND	Default value of sound standard in APS menu 0-> BG 1-> I 2-> DK 3-> L\L'	0-3	0

Table 13 Factory Service settings

2.3.1. TUNER Settings

	AK56 SERVICE MENU ITEMS							
	B1-H	B1-L	B2-H	B2-L	BS1	BS2	BS3	CB
Philips UV1316S MK3	12	50	30	2	1	2	4	142
LG TAEW-G002D	11	82	29	2	1	2	8	142
Thomson CTT5020	9	146	27	130	3	6	133	142
Samsung TECC2949PG28B	13	18	31	130	1	2	4	142
Samsung TECC2949PG35B	13	18	30	130	1	2	8	142
Alps TEDE9X226A	11	82	29	2	1	2	8	142
Alps TEDE9-004A	11	194	28	242	1	2	8	142
Samsung TECC2949PG40B	11	82	29	2	1	2	8	142
Samsung TECC2949PS40B	11	82	29	2	1	2	8	142