

2. Použití odchylkových obrazovek

Typ TVP	Číslo ZD 6PN	Pozice	Norma	RH č.	RH č.	RH č.	RH č.	RH č.
			A 48 EEV 13x0,1	A 48 EAX 13x01				
107 112	6PN 387 377 387372	C 404 C 408 U zdroj U VN	TC 343 8n2 KV 330p/2kV 118+/-0,5V 24 - 25,5 kV	TC 344 7n5 nejde 118 +/-0,5V 24 - 25,5 kV				
			A 48 EEV 13x0,1	A 48 ECR 31x60	A 48 ECR 11x60	A 48 EAX 13x0,1		
51 M 487 51 M 487-40	6PN 387 329 387345	R 432 R 349 C 410 C 404 C 407 C 408 L 403 R 413 U 2 U a	TR 296 22k/J TR 213 390R/K TC 330 470n/J TC 343 8n2/J KV1 330p/M KV1 330p/M 6PK 614 109 TR 215 1R2/J 118V +/-0,5V 24 - 25 kV	TR 296 24k/J TR 213 390R/K TC 330 390n/J TC 343 9n1/J KV1 330p/M Neosazovat 6PK 614 109 TR 215 1R2/J 121 V 24 - 25 kV	TR 296 22k/J TR 213 560R/K TC 330 470n/J TC 343 9n1 KV1 330p/M Neosazovat 6PK 614 109 TR 215 1R2/J 120V +/-0,5V 24 - 25 kV	NR NR NR TC 344 7n5/J NR Neosazovat NR NR NR NR		
			A 51 ALE 55x01	A 51 EBV 13x01	A 51 EFS 83x191			
470 - 50 485 - 50	387 355 387 363	T 101 T 401 L 403 C 410 V 404 R 416 C 407, 408 U - zdroj U VN U g2	6PN 350 57 1192 0447 6PK 614 109 MKP 390 nF TC 344 8n2 TR 215 2R7 Osadit 126 V 26,8 - 28,3 kV 125 + 5V/ -0V	NR NR NR NR TC 343 6n8 TR 1215 1ROK Osadit 124 V 26,8 - 28,3 kV NR	NR NR NR NR TC 344 8n2 TR 215 1ROK C 407 vypustit 126 V NR NR			
			A 34 EFU 33x91	A 34 EAC 01x06				
4347 A	6PN 387 296	R 416 R 432 R 439 T 401 C 404 L 403 U 2 Ua VN	6PK 614 113 TR 296 22k/J TR 213 560R/K 1142.0735 C TC 344 8n2/J 6PK 614 109 109V +/- 0,5V 22,5 - 24,2 kV	TR 215 1R5/J TR 296 24k/J TR 213 390R/K DST 1142.0635 TC 343 7n5/J 6PK 614 109 109V +/- 0,5V 22,5 - 24,2 kV				
Typ TVP	Číslo ZD 6PN	Pozice	Norma	RH č.	RH č.	RH č.	RH č.	RH č.

			A 34 EAC 01x06	A 34 EFU 33x91				
37 P 101 - 5 37 P 101 AB	387 365 387 354	T 101 T 401 L 403 C 410 C 404 R 416 C 407 U zdroj V VN	6PN 350 56 1142 635 C 6PK 614 109 MKP 470nF TC 343 6n8/J TR 215 1R5 Osadit 109 V 22,5 - 24,2 kV	NR 1142 0735 NR NR TC 344 7n5/J 6PK 614 113 Neosazovat 109 V 22,5 - 24,2 kV				

			A 41 EAM 4 0x01					
349 45 P 105 AB 4345	387 318 387 351 387 278	T 101 T 401 L 403 C 404 R 416 U zdroj U VN	6PN 350 56 1142.635 6PK 614 109 TC 343 6n8 TR 215 1R5 109 V 23 - 24,5kV					

				India				
			A 51 ALE 55x01	151 JSY 61x30				
55 B 106 55 M 2108 55 B 111	6PN 387 359 387 364 387 371	R 416 C 407 C 404	TR 215 2R7/J KV1 330pF/M TC 344 8n2/J VN 27,5+/-0,8kV U2 126V					

			A 59 ECF 20x01	A 59 TMZ 40x01	A 59 EAK071x01	A 59 EAK 71x01		
471 472 492	6PN 387 302 387 304 387 346	R 203 R 204 R 444 C 522 L 202 C 229 R 237 L 205 U - zdroj U VN	TR 245 24k/J TR 245 6k8/J TR 245 10k/J B 32529 22n/100 AT 4042/90 TC 344 1nK/2kV TR 245 12K/J 6PK 614 84 158 +1V/-1,5V 27,0 +0,5/-0,7kV	TR 245 1K3/J TR 245 750R/J TR 245 11K/G K5T 1nS AT 4042/90 T KV1 330p/2kV NR NR 158V +/-0,5V 27,0 +/-0,7kV	NR NR TR 245 11k G NR NR NR TR 245 11K G TR 215 1R5 160V +/-0,5V 27,5 +/-0,8kV	NR NR NR NR NR NR TR 245 11K G NR 160 +/-0,5V 27,5 +/-0,8kV		

Typ TVP	Číslo ZD 6PN	Pozice	Norma	RH č.	RH č.	RH č.	RH č.	RH č.
			A 51 ALE 55x01	A 51 EBV 13x01	A 51 EFS 43x191	A 51 EFS 83x19		
55 B 106	387 359	R 416	TR 2315 2R7/J	TR 215 1R0/K	TR 215 1R0/K	TR 215 1R0/K		

55 M 113	387 371	C 408	KV1 330p/M	NR	NR	NR		
55 M 108	387 364	C 407	KV1 330p/M	NR	NR	Ruší se		
55 B 111	387 371	C 404	TC 344 8n2/J	TC 343 6n8/J	TC 343 6n8/J	TC 344 8n2/J		
		U - zdroj	126 V	124 V	124 V	126 V		
		Ug2	125 +5V/-0V	NR	NR	127 NR		
		C 711	K5T 18pF	K5T 27pF	NR	128 NR		
		Ua - VN	27,5 +/-0,8kV	NR	NR	129 NR		

			A 51 EAL 55x0,1	A 51 EBV 13x0,1	A 51 EFS 43x191	A 651 EFS83x191		
--	--	--	------------------------	------------------------	------------------------	------------------------	--	--

506	6PN 387 337	C 408	KV1 330pF/M	NR	Ruší se	Ruší se		
		C 412	TC 343 8n2/J	TC 343 6n8/J	TC 343 8n2/J	NR		
		R 422	Jde na L 404	TR 243 0,22R/J	TR 243 0,22R/J	TR 243 0,22R/J		
		R 442	TR 157 4R7/J	TR 157 10R/J	TR 157 4R7/J	NR		
		R 413	WK66951 6R8/J	TR 243 OR 47	NR	NR		
				(dva do série)				
		L 404	6 PK 614 84	Ruší se	TR 243 0,22R/J	TR 243 0,22R/J		
		U - zdroj	126 +/-0,5V	124 +/-0,5V	126 +/-0,5V	126 +/-0,5V		
		U VN	27,5 +/-0,8kV	27,5 +/-0,8kV	27,5 +/-0,8kV	27,5 +/-0,8kV		
		Ug2	125 V +5V/-0V	110 V	125V -sig.bílá	125V +0V/-5V		
		R 744	TR 245 2k4/J	TR 218 1k8/J	TR 245 2k4/J	TR 245 2k4/J		

			A 59 ECF 20x01	A 59 EAK071x01	A 59 EAK 71x01	A 59 TMZ 40x01	A 59 ECF 20x12	A 59 ECF 50x12
--	--	--	-----------------------	-----------------------	-----------------------	-----------------------	-----------------------	-----------------------

500	6PN 387 335	R 233	TR 245 12K/G	NR	NR	NR	TR 245 10K/G	TR 245 10K/G
		R 442	TR 157 10R/J	Ruší se	Ruší se	TR 157 10R/J	TR 157 4R7/J	TR 157 4R7/J
501	387 336	R 407	TR 157 4R7/J	TR 175 33R/J	TR 157 33R/J	TR 157 4R7/J	TR 157 4R7/J	TR 157 33R/J
502	382 352	C 414	MKP390nJ/250V	MKP1841 360nJ	MKP1841 360nJ	NR	MKP 470nJ/250	MKP 1841 470nJ
503	382 353	R 444	TR 334 100R	TR 234 270R/J	TR 233 270R/J	TR 234 270R/J	TR 234 270R/J	TR 234 270R/J
512	382 352	L 401	AT 4042/90	LC 110/92	AT 4042/90	AT 4042/90	AT 4042/90	NR
513	382 353	C 412	TC 344 9n1/J	NR	NR	NR	TC 343 10n/J	TC 343 10n/J
		C 413	TC 341 27n/J	NR	NR	TC 342 22n/630	TC 341 27nJ/630	NR
		U - zdroj	160 +/-0,5V	160 +/-0,5V	160 +/-0,5V	160 +/-0,5V	152,5 +/-0,5V	152 +/-0,5V
		U VN	27,5 +/-0,8kV	27,5 +/-0,8kV	27,5 +/-0,8kV	27,5 +0,5/-0,8kV	27,5 +/-0,8kV	27,5 +/-0,8kV
		T 101	6PN 350 67	NR	NR	NR	6PN 350 67.1	6PN 350 67.1
	Pozice platí pro všechny TVP	R 744	TR 245 2k4/J	TR 245 2k4/J	TR 245 2k4/J	TR 245 2k4/J	TR 218 1K8/J	TR 218 1K8/J
		Ug2	125 +5/-0V	125 +5/-0V	125 +5/-0V	125VŠŠ +5V-0V	110V +5/-0V	110VŠŠ +5/-0V

Typ TVP	Číslo ZD 6PN	Pozice	Norma	RH č.	RH č.	RH č.	RH č.	RH č.
---------	--------------	--------	-------	-------	-------	-------	-------	-------

			A 66 ECF 20x01	A 66 EMZ 43x01	A 66 EAK 071x01	A 66 ECF 40x01	A 66 ECY 13x31	
--	--	--	-----------------------	-----------------------	------------------------	-----------------------	-----------------------	--

474	6PN 387 305	R 203	TR 245 6k8J	TR 245 1k2J	NR	NR	NR	
4488	387 306	R 204	TR 245 2k2J	TR 245 680RJ	NR	NR	NR	
		R 228	TR 245 1R2J	TR 245 4R7J	NR	NR	NR	

		R 311	TR 245 10kJ	TR 245 6k8J	NR	NR	NR	
		R 332	TR 245 680R/J	TR 245 820R/J	NR	TR 245 820R/J	NR	
		R 333	TR 245 680R/J	TR 245 820R/J	NR	TR 245 820R/J	NR	
		R 334	TR 245 680R/J	TR 245 820R/J	NR	TR 245 820R/J	NR	
		R 502	TR 214 330k/J	TR 214 390k/J	NR	TR 214 390K/J	NR	
		C 229	TC 344 1nK/2kV	KV1 330p/2kV	NR	KV1 330p/2kV	NR	
		L 202	AT 4042/90	AT 4042/90T	NR	NR	NR	
		L 205	6PK 614 84	TR 215 1R5	NR	TR 215 1R5	TR 215 0R47/K	
		R 325	TR 296 4R7/J	NR	TR 296 3k9/J	NR	NR	
		R 326	TR 296 4R7/J	NR	TR 296 3k9/J	NR	NR	
		R 327	TR 296 4R7/J	NR	TR 296 3k9/J	NR	NR	
		R 209	TR 296 270R/J	NR	NR	NR	TR 296 180R/J	
		U - zdroj	158V +1V	160V +/-0,5V	158 V	158 + 1V	158 V	
		U VN	27,0 +0,5/-0,7kV	27,0 +/-0,5kV	27,0 +0,5/-0,7kV	27,0 +0,5/-0,7kV	27,0 +0,5/-0,7kV	
		R 701	TR 296 +k2/J	TR 296 1k2/J	TR 296 820R/J	TR 296 820R/J	TR 296 1k2/J	
		R 237	TR 245 12k/J	TR 245 12k/J	TR 245 12k/J	TR 245 12k/J	TR 296 11k/G	
		R1 na VJ	TR 234 390R/K	TR 234 390R/K	TR 234 390R/K	TR 234 390R/K	Zrušit	

			A 51 EAL 55x01	A 51 EBV 13x01	A 51 EFS 43x191	A 51 ECQ 10x01	A 51 EFS 83x19	
462	6PN 387 281	T 101	6PN 350 57	NR	NR	NR	NR	
463	387 279	T 401.2	1192.04478	NR	NR	NR	NR	
473	387 317	T 401.1	M 12-28	NR	NR	NR	NR	
484		R 421.2	TR 233 3R3/K	NR	NR	NR	NR	
		R 421.1	TR 296 1R0/J	NR	NR	NR	NR	
		R 416	TR 215 2R7	TR 215 1R0/K	TR 215 1R0/J	TR 215 2R2/K	TR 215 1R0/J	
		C 404	TC 343 8n2	TC 343 6n8/J	TC 344 7n5/J	NR	TC 344 7n5/J	
		L 403	6PK 614 109	NR	NR	96PK 614 95	NR	
		U - zdroj	126 V	124 V	124 V	126 V	124V +/-0,5V	
		Ua VN	27,5 +/-0,8kV	27,5 +/-0,8kV	NR	27,5 +/-0,8kV	27,5 +/-0,8kV	
		Ua VN	26,4-28,3kV	26,4-28,3kV	NR	26,4-28,3kV	NR	
			Nokia-Split/kV/	Nokia-Split/kV/	NR	Nokia-Split	NR	
		Ug2	140 V	NR	NR	NR	NR	

Typ TVP	Číslo ZD 6PN	Pozice	Norma	RH č.	RH č.	RH č.	RH č.	RH č.
---------	--------------	--------	-------	-------	-------	-------	-------	-------

			A 66 EAK 71x01	A 66 EMZ 43x01	A 66 ECF 50x12			
505	6PN 387 358	R 233	TR 245 12k/G	NR	TR 245 10K/G			
504	6PN 387 357	T 101	6PN 350 67	NR	6PN 350 67.1			
		R 422	TR 157 10R/J	Ruší se	TR 157 4R7/J			
		R 407	TR 157 33R	TR 157 4R7/J	TR 157 33R/J			
		C 413	TC 341 27nJ/630	TC 341 22nJ/630	TC 341 27nJ/630V			

		L 401 C 412 C 414 U - zdroj U VN Ug2 R 744	LC 110/92 TC 344 9n1/J MKP 1841 390n/J 160 V 27 +0,5/0,8kV 125V +5/-0V TR 245 2k4/J	AT 4042/90T NR NR 160V +/-0,5V 27 +0,5/0,8kV 125V +5/-0V TR 245 2k4/J	LC 110/92 TC 343 10nJ/630 MKP 1841 470n/J 152V +/-0,5V 27 +0,5/0,8kV 110V +5/-0V TR 218 1k8/J			
--	--	--	---	---	---	--	--	--

India

		A 48 EEV 13x01	A 48 JSK 61x01					
51 M 112 51 M 107	6PN 387 372 387 377	C 404 C 408 C 407 R 411 Ua Ug2	TC 343 8n2/J KV1 330pF/M KV1 330pF/M TR 214 68k/J 24 - 25,5 kV 118V +/-0,5V	TC 343 8n2/J NR Neosazovat TR 214 82k/J 24 - 25,5 kV 118V +/-0,5V				